

Point ID Flow

The following rules determine if an alarm will get the Zone Description or the Point ID Description.

If the Programming exists in the Customer Transmitter programming:

- Then use the Point ID associated with that event.
 - If there is no associated Point ID in the Customer Programming
 - Then use the Zones to find the description that matches the zones.

If the Programming does NOT exist in the Customer Transmitter programming and DOES exist in the assigned Transmitter type:

- Then use the description in the Customer Zones
 - If there is no description in the Customer Zones
 - Then use the Point ID of the event in the Transmitter Type form

If the Programming does NOT exist either at the Customer or Transmitter programming:

- Then use the zone description on the Customer Zones form



Additional Rules:

If the “Zone Fill” option is turned on (Add/Update Always or Add/Update when On Test), the panel’s Point ID (when available) will be applied as the zone description. The order is as follows:

- Customer’s Transmitter Programming Point ID
- Zone Description
- Transmitter Type’s Programming Point ID
- Panel’s Point ID

