

SIMS III for Windows – Adding a New Operator

The following details adding a new operator through SIMS III for Windows. (this can be done by a user with MGT access only)

Instructions:

1. Go to Edit>Table Maintenance>Operator Maintenance.
2. Click on Insert to add a new Operator.

Name	Initials	ID	Group	Level	Access Level
ALF	alf	1a2b3c4f	182@	WEB	&1234567d
Apprentice Example	SIM	999		APR	*
David	dav	777		WEB	&123456abc
dixie	dav	123	ACM?	WEB	&'abcdefghi
iPhone Account Login	WB1	Password		WEB	&*dU
iPhone Account Login	WB2	Password		SUP	\$1234567d
iPhone Dir ACME Lo...	SIM	006		WEB	&1234567d
iPhone Dir SIMS Login	SIM	007		WEB	&1234567d
iPhone Login	SIM	005		WEB	&1234567

3. Once the new line appears, then enter the Name, Initials and Password (which can be up to 8 alpha-numeric characters each). The Group field will allow the Operator to be set to view/handle only accounts belonging to that Group. If it is left blank, then that Operator will have access to all accounts in the database.
4. The next field to be chosen is the Access Level (which has multiple drop down options).
 - Remote Level (Terminal Services User)
 - Web-Access Level (SIMSWeb and iPocket User)
 - Apprentice Level
 - Operator Level
 - Supervisor Level
 - Master-Supervisor Level
 - Management LevelEach level from Apprentice to Management includes the access from the previous level.



Additional Information:

- For expanded information see the SIMS III for Windows – Operator Access Levels Quick Reference Guide.

How to Add a New Operator (cont.)

- To enable all options on the Access Level, enter a * into the Access field. To only enable specific features, click on the Definitions button and only enable the features desired.

The screenshot shows the 'Operator Maintenance' window with a table of operators. The 'Access' field for the selected operator is highlighted with a black box. Below the table, the 'Definitions' button is also highlighted. A sub-window titled 'SIMS II Apprentice Level' is open, showing a list of features with checkboxes, all of which are checked. The 'Toggle' button is highlighted in this sub-window.

Name	Initials	ID	Group	Level
ALF	alf	1a2b3c4f	182@	REM
Apprentice Example	SIM	999		APR
David	dav	777		WEB
dixie	dav	123	ACM?	WEB
iPhone Account Login	WB1	Password		WEB
iPhone Account Login	WB2	Password		SUP
iPhone Dlr ACME Login	SIM	006		WEB
iPhone Dlr SIMS Login	SIM	007		WEB
iPhone Login	SIM	005		WEB

Operator Maintenance

Insert
Delete
Print

Definitions

Name: Apprentice Example, Initials: SIM, Password: 999, Group: [], Access Level: Apprentice Level

Access: [], Last Update: 01/02/19, IP Mask: []

SIMS II Apprentice Level

- Select Language
- Action Mask OUS
- Manual Alarm
- Complete Alarm Event
- View Pending WorkOrders
- Generate WorkOrder
- Workorder History
- About SIMS
- Interface Display
- Phone Notepad
- Operator Log Msgs
- Program Status
- Computer Status
- Disk Drive Status
- Status of Account
- History Files Available
- Historical Reports

Toggle OK Cancel

- If more than one operator is entered, then the user can hit Apply between making changes. Once all changes are done, then click on OK.